

# StorEdge™ Single Phase Inverter for Australia

SE3000-AUS / SE5000-AUS / SE6000-AUS



STOREDGE™

## Ideal for battery storage and backup power

- Supports StorEdge Solution Applications** - reduce electric bills with maximised self-consumption and profile programming
- Enhanced Safety** - designed to eliminate high voltage during installation, maintenance or firefighting
- Provides Backup Power** - StorEdge Inverter includes the hardware required for automatically supplying power to backed-up loads in the event of grid outages
- Full Visibility** - built-in monitoring of battery status, PV production, remaining backup power, and self-consumption data
- Simple Design and Installation** - single inverter for managing PV production, battery storage and backup power
- Easy Maintenance** - remote access to inverter software

# / StorEdge™ Single Phase Inverter for Australia

SE3000-AUS<sup>(1)</sup> / SE5000-AUS<sup>(1)</sup> / SE6000-AUS<sup>(1)</sup>

	SE3000-AUS	SE5000-AUS	SE6000-AUS	UNIT
<b>OUTPUT - AC (LOADS/GRID)</b>				
Rated AC Power Output	3000	4985	6000	VA
Max AC Power Output	3000	4985	6000	VA
AAC Output Voltage (Nominal), L-N(2)	220 / 230			Vac
AC Output Voltage Range, L-N	184 - 264.5			Vac
AC Frequency	50 / 60 ± 5			Hz
Maximum Continuous Output Current	14	27		A
Residual Current Detector / Residual Current Step Detector	300 / 30			mA
Utility Monitoring, Islanding Protection, Country Configurable Thresholds	Yes			
Charge Battery from AC (if Allowed)	Yes			
THD	<3			%
Power Factor With Rated Power	>0.99 (configurable; 0.8 leading to 0.8 lagging)			
Typical Nighttime Power Consumption	<5			W
<b>OUTPUT - AC (BACKUP POWER)<sup>(3)</sup></b>				
Rated AC Power Output	Lower of: 4985, battery max power			VA
Max AC Power Output - Surge	Lower of: 6600, battery max power			VA
AC Output Voltage (Nominal)	220 / 230			Vac
AC Output Voltage Range	184 - 264.5			Vac
AC Frequency	50 / 60 ± 5			Hz
Maximum Continuous Output Current	22			A
AC Breaker	Yes			
THD	<5			%
Power Factor With Rated Power	0.2 leading to 0.2 lagging			
Automatic Switchover Time	<2			sec
<b>INPUT - DC (PV AND BATTERY)</b>				
Transformer-less, Ungrounded	Yes			
Max Input Voltage	500			Vdc
Nom DC Input Voltage	400			Vdc
Reverse-Polarity Protection	Yes			
Ground-Fault Isolation Detection	600kΩ Sensitivity			
Maximum Inverter Efficiency	97.6			%
European Weighted Efficiency	97.4			%
<b>INPUT - DC (PV)</b>				
Maximum DC Power (STC)	4050	6750	8100	W
Additional DC Power for DC Coupled StorEdge Systems	kWp equivalent of battery continuous power, and no more than 5kWp			
Max Input Current	19.5		23	Adc
2-pole Disconnection	Yes			
<b>INPUT - DC (BATTERY)</b>				
Compatible Batteries	LG Chem RESU7H LG Chem RESU10H			
Peak Power	LG Chem RESU7H: 5000, LG Chem RESU10H: 7000			W
Number of Batteries per inverter	1 or 2 <sup>(4)</sup>			
Continuous Power	LG Chem RESU7H: 3500, LG Chem RESU10H: 5000			W
Max Input Voltage	500	1000		Vdc
Max Input Current	17.5			Adc
DC Fuses on Plus and Minus	25A (field replaceable)			
<b>ADDITIONAL FEATURES</b>				
Supported Communication Interfaces	RS485 for battery, RS485, Ethernet, ZigBee (optional), Wi-Fi (optional)			
Battery Power Supply	12V / 53W			
Integrated AC, DC and Communication Connection Unit	Yes			
AC Disconnect	Yes			
Manual Inverter Bypass Switch	Yes			
DC Voltage Rapid Shutdown (PV and Battery)	Yes, according to VDE 2100-712 (pending)			

<sup>(1)</sup> These specifications apply to inverters with part numbers SEXXXX-AUS2XXXXX

<sup>(2)</sup> The StorEdge Inverter must be connected Line to Neutral (and not Line to Line)

<sup>(3)</sup> Not designed for standalone applications and requires AC for commissioning

<sup>(4)</sup> When connecting two LG Chem batteries, each battery must have a different part number; supporting SolarEdge firmware required

# / StorEdge™ Single Phase Inverter for Australia

SE3000-AUS<sup>(1)</sup> / SE5000-AUS<sup>(1)</sup> / SE6000-AUS<sup>(1)</sup>

STANDARD COMPLIANCE (PENDING)		
Safety	IEC-62103 (EN50178), IEC-62109	
Grid Connection Standards <sup>(5)</sup>	VDE 0126-1-1, NRS 097-2-1, AS4777	
Emissions	IEC61000-6-2, IEC61000-6-3, IEC61000-3-11, IEC61000-3-12	
INSTALLATION SPECIFICATIONS		
AC Output (Loads/Grid) conduit size / wire cross section	32mm / 4-14mm <sup>2</sup>	
AC Output (Backup) conduit size / wire cross section	25-32mm knockout / 4-14mm <sup>2</sup>	
DC Input (PV) conduit size / wire cross section	25mm / 4-6mm <sup>2</sup>	
DC Input (Battery) conduit size / wire cross section	25mm / 4-6mm <sup>2</sup>	
Dimensions with Connection Unit (HxWxD)	962 x 315 x 184	
Weight with Connection Unit	26.5	
Cooling	Natural convection and internal fan (user replaceable)	
Noise	<50	
Min - Max Operating Temperature	-20 to +60 <sup>(6)</sup>	
Protection Rating	IP65 - Outdoor and Indoor	

<sup>(5)</sup> For all standards refer to Certifications category in Downloads page: <http://www.solaredge.com/groups/support/downloads>

<sup>(6)</sup> Power derating from 50 °C

# / StorEdge™ Single Phase Inverter for Australia

SE3000-AUS / SE5000-AUS / SE6000-AUS

## StorEdge Solution with Backup Power

